LUCASEY® MOUNTING SYSTEMS

LC2X2WT
Security Wall Mount with Tilt for up to 32" Flat Screens



The LC2X2WT Security Wall Mount with Tilt is designed to secure up to a 32" flat panel monitor to the wall while still allowing the monitor to tilt.

The VESA® mounting patterns on the front of the LC2X2WT allow it to be mounted to monitors that have mounting patterns of 200mm x 100mm and 100mm x 100mm.

Convenient cutouts for electrical and A/V wiring in the wall.

The security screws provided with the mount can be used to prevent easy removal of the monitor without having the appropriate security tool (purchased separately). Standard socket head screws are also provided to mount the monitor without using the security hardware.

Our mounts are tested at four times the rated load limit to ensure that they can hold the monitor during seismic or other extreme loading events.

Important! Please read all warnings and cautions before installing the mount.

Caution: Improper installation of this mount may void the warranty on your monitor.

Caution: Wall attachment should be performed by qualified installers only, using construction methods prescribed by authorized architects or engineers that comply to all applicable codes and standards.

The maximum weight of monitor to be installed on the LC2X2WT is 75 Lbs. (34.1Kg.)

Inspect all parts to make sure there is no shipping damage. Do not install if any parts are damaged.

Please call 1-800-LUCASEY or 1-510-534-1435 if you have any questions about this installation.

Protected under one or more of these U.S. Patent numbers: 3,291,432 3,559,942 3,724,798 DES.270,689 4,613,109 4,878,645 4,852,842 DES.309,562 4,973,023 5,169,114 5,255,884 5,310,152 5,522,576 5,621,614 Re.35,677 DES.398,834 5,826,384 5,941,492 5,964,068 6,060,661 6,102,398 6,158,704 6,454,116B1 6,761,276B2 6,806,425B1

©2009 Lucasey Manufacturing Corporation, Oakland, California

WARNING: Improper installation can result in serious personal injury. It is the responsibility of the installer to ensure that all safety precautions are taken during the installation and that all safety features of the mount are properly utilized.

WARNING: The structure to which the mount is attached needs to be capable of supporting five times the stated load limit. Additional reinforcement of the structure may be necessary and a certified architect or engineer is needed to make this determination.

WARNING: Take into consideration the combined weight of the mount, the monitor and any auxiliary equipment when determining the total load on the wall and mount.

WARNING: Do not place your fingers between movable parts on the LC2X2WT mount. The LC2X2WT Back Plate and VESA Mounting Plate, when adjusting the tilt or putting the monitor in place, create pinch points that can cause injury.

WARNING: Make sure that the screws used to attach the monitor to the mount are the appropriate size and length. An assortment of monitor attaching screws are provided for convenience. The appropriate screws to use for mounting the monitor is determined by the monitor manufacturer. Failure to use the screws recommended by the monitor manufacturer can result in the monitor dropping from the mount and/or damage to the electronic components inside the monitor.

Table of Contents

Page 1 ... Title Page & Product Description
Page 2 ... Warnings, Item List & Tools Required
Page 3 ... Dimensional Drawings
Page 4 ... Installation Instructions forLC2X2WT Wall Plate
Page 5 ... Installation Instructions for Monitor Attachment
Page 6 ... Tilt Adjustment, Monitor Removal & Warranty

Tools Required

Stud Finder
Drill with 1/8"Drill Bit
Phillips Screw Driver
1/4" Socket Driver w/ 1/4" Socket
1/4"Socket Extension 12" - 16"
5/32" Hex Driver for 1/4" Socket

(optional security tool 5/32" Hex Driver with hole for 1/4" Socket)

Item List

1 ... LC2X2WT Wall Plate
1 ... LC2X2WT VESA Mounting Plate
8 ... #10-24 x 1" Socket Head Cap Screws
4 ... #10-24 x 3/8" Button Head Screw with Security Pin
3 ... #14 x 2-1/2" HWH Lag Screws

Monitor Attaching Screw Assortment

6 ... 4mm x 25mm Set Screws
12 ... 4mm Hex Nuts
6 ... 5mm x 30mm Set Screws
12 ... 5mm Hex Nuts
6 ... 6mm x 30mm Set Screws
12 ... 6mm Hex Nuts
6 ... 4mm x 12mm Phillips Screws
36 ... 5mm Flat Washers
6 ... 5mm x 12mm Phillips Screws
18 ... 1/4" Flat Washers
6 ... 6mm x 12mm Phillips Screws

Protected under one or more of these U.S. Patent numbers: 3,291,432 3,559,942 3,724,798 DES.270,689 4,613,109 4,878,645 4,852,842 DES.309,562 4,973,023 5,169,114 5,255,884 5,310,152 5,522,576 5,621,614 Re.35,677 DES.398,834 5,826,384 5,941,492 5,964,068 6,060,661 6,102,398 6,158,704 6,454,116B1 6,761,276B2 6,806,425B1

©2009 Lucasey Manufacturing Corporation, Oakland, California

LUCASEY MOUNTING SYSTEMS

VESA Mounting Plate



Side View



Isometric View



Wall Plate



Tilted Side View



Top View



Protected under one or more of these U.S. Patent numbers: 3,291,432 3,559,942 3,724,798 DES.270,689 4,613,109 4,878,645 4,852,842 DES.309,562 4,973,023 5,169,114 5,255,884 5,310,152 5,522,576 5,621,614 Re.35,677 DES.398,834 5,826,384 5,941,492 5,964,068 6,060,661 6,102,398 6,158,704 6,454,116B1 6,761,276B2 6,806,425B1

©2009 Lucasey Manufacturing Corporation, Oakland, California









Wood Stud Installation

Determine the best possible viewing location for your monitor taking into account the tilt angle to be used.

Locate a wood stud using a stud finder in the location where the monitor is to be mounted.
Note: The LC2X2WT can be mounted on the stud with the mount centered or offset to the left or right 4". (Optional Toggle Bolts are required for offset installations or metal stud installations)

Use the LC2X2WT Back Plate as a template to mark the locations for three pilot holes in the wood studs.

Drill 1/8" pilot holes in the three marked locations.

Use the provided #14 x 2-1/2" Lag Screws to attach the LC2X2WT Back Plate to the wall.

Metal Stud Installation

(Using optional WMATB3 Toggle Bolt Kit)

Determine the best possible viewing location for your monitor taking into account the tilt angle to be used.

Locate a stud using a stud finder in the location where the monitor is to be mounted.

Follow the instructions that come with the toggle bolt kit to install the toggle bolt plastic retainers at each of the three mounting hole locations.

Use the Screws provided with the toggle bolt kit to attach the LC2X2WT Back to the wall.

Protected under one or more of these U.S. Patent numbers: 3,291,432 3,559,942 3,724,798 DES.270,689 4,613,109 4,878,645 4,852,842 DES.309,562 4,973,023 5,169,114 5,255,884 5,310,152 5,522,576 5,621,614 Re.35,677 DES.398,834 5,826,384 5,941,492 5,964,068 6,060,661 6,102,398 6,158,704 6,454,116B1 6,761,276B2 6,806,425B1

©2009 Lucasey Manufacturing Corporation, Oakland, California





Monitor Attachment to Front Plate

Determine which type of monitor attaching hardware is required for the monitor as specified by the monitor manufacturer. Various sizes of monitor attaching screws are provided for convenience.

Make sure the top of the LC2X2WT Front is oriented in the same direction as the top of the monitor. The holes on the side of the LC2X2WT Front Plate are closer to the bottom edge than the top edge.

Align the LC2X2WT front plate with the VESA mount pattern on the back of the monitor. Attach the LC2X2WT Front Plate to the back of the monitor using the appropriate size screws and washers.

Make sure all of the Monitor Attaching Screws are tight before proceeding with the rest of the installation.

Attaching Front Plate to Back Plate

Screw four of the provided Socket Head Screws into the threaded inserts closest to the monitor on the LC2X2WT Front. Leave 1/2" of thread exposed.

With two people, lift the monitor, with attached LC2X2WT Front, onto the LC2X2WT Back making sure that the Socket Head Screws are engaging the Mounting Slots.

Using a long extension and the appropriate security socket tool or socket head driver, insert the Tilt Adjusting Screws and Pivot Screws into the threaded inserts farthest from the monitor.

Remove the Socket Head Screws, only after making sure the Tilt Adjusting Screws and Pivot Screws are installed. Adjust the tilt to the desired viewing angle and tighten all four screws.

Note: Security Screws and Socket Head Screws are provided for convenience. Either can be used to safely install the mount.

Protected under one or more of these U.S. Patent numbers: 3,291,432 3,559,942 3,724,798 DES.270,689 4,613,109 4,878,645 4,852,842 DES.309,562 4,973,023 5,169,114 5,255,884 5,310,152 5,522,576 5,621,614 Re.35,677 DES.398,834 5,826,384 5,941,492 5,964,068 6,060,661 6,102,398 6,158,704 6,454,116B1 6,761,276B2 6,806,425B1

©2009 Lucasey Manufacturing Corporation, Oakland, California





Monitor Removal

Adjust the monitor tilt to 0 ° and insert four Socket Head Screws into the threaded inserts closest to the monitor.

Remove the Tilt Adjustment Screws and the Pivot Screws.

Lift the monitor with attached LC2X2WT Front and separate the front from the back. Carefully set the monitor down and remove the monitor attaching screws.

Tilt Adjustment

Loosen the Tilt Adjusting Screws

Tilt the monitor to the desired viewing angle.

Tighten the Tilt Adjusting Screws.

LIMITED WARRANTY

LUCASEY MANUFACTURING CORPORATION MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED except that the goods sold under this agreement shall be free of defects in materials and workmanship for a period of one year from the user's date of purchase. User assumes all risk and liability resulting from the use of the goods, whether used singly or in combination with other goods. Lucasey Manufacturing Corporation neither assumes nor authorizes any person to assume for it any other liability in connection with the sale or use of the goods sold and there are no oral agreements or warranties collateral to or affecting this limited warranty. Lucasey Manufacturing Corporation will repair or replace defective parts or equipment within one year of the date of purchase, at its option, provided the part or equipment is returned pre-paid to Lucasey Manufacturing Corporation's plant. The repaired or replaced part shall be shipped to the user, FOB Lucasey Manufacturing Corporation's plant. NO allowance for outside labor charges are implied within the terms of this limited warranty. Under no circumstances will Lucasey Manufacturing Corporation be responsible for special, indirect or consequential damages. The remedies set forth in this Limited Warranty are exclusive and the liability of Lucasey Manufacturing Corporation with respect to any contract of sale or anything done in connection therewith, whether in contract, in tort, under any warranty or otherwise shall not, except as expressly provided herein, exceed the price of the equipment or part on which such liability is based. Any damage caused by the improper use, operation beyond capacity, substitution of parts or equipment not approved by Lucasey Manufacturing Corporation, improper packaging, failure to observe installation or other instructions, transit, or repair by one other than Lucasey Manufacturing Corporation, will not be covered by and shall void this Limited Warranty.

Protected under one or more of these U.S. Patent numbers: 3,291,432 3,559,942 3,724,798 DES.270,689 4,613,109 4,878,645 4,852,842 DES.309,562 4,973,023 5,169,114 5,255,884 5,310,152 5,522,576 5,621,614 Re.35,677 DES.398,834 5,826,384 5,941,492 5,964,068 6,060,661 6,102,398 6,158,704 6,454,116B1 6,761,276B2 6,806,425B1

©2009 Lucasey Manufacturing Corporation, Oakland, California